

## EMERGENCY PROGRAM PLAYER SD CARD



The new REP-02 SD card program player from Elan Audio is an improved version of the REP-01 that is plug compatible.

### Standard features are:

- SD card player.
- SD and SDHC card support, FAT16 or FAT32
- Mp3 and WAV playback
- Sequential or random play and many other play options
- Stereo balanced out
- Mono balanced out
- Pre-emphasised mono out (Composite mono)
- Rear DIP switch settings for basic mode selection
- USB port for external control, advanced settings and bootloader
- Left and Right output level trims on rear.
- Run control inputs, GND to operate and Inject to operate
- 240V 50Hz power supply
- DB Connector "Easy" link to RPF-02/RPF-03 units.
- TEST and STEP controls for testing player
- Rotary switch and ENTER switch to control 16 x 2 line backlit LCD
- Stereo headphone socket with volume control
- OK, RUN, TEST, LAN and POWER front panel indicators
- Audio outputs muted when testing cards from front panel

### Current Options:

#### **AES Digital out**

The AES Digital output option uses the Mono balanced output socket.

The AES output is 24bit at either 48 or 96KHz.

#### **Ethernet LAN**

This option provides status, control and the ability to remotely manage the audio files on both cards, including uploading of audio files.

#### **Stereo MPX Encoder**

This option provides stereo composite audio suitable to broadcast in stereo. This module also has an adjustable Limiter and AGC stage